



# Antenna Reference Guide

Version 4  
April 2021





## Disclaimer

This Antenna Reference Guide (the “Guide”) is provided by Cradlepoint, Inc. (“Cradlepoint”) to assist its Distribution Partners (“Partners”) with the selection and installation of third-party antennas with Cradlepoint hardware. This Guide and mention of third-party products are for informational purposes only and do not constitute affiliation with, recommendation or endorsement of, any third-party or its products.

All third-party product specifications and descriptions are supplied by the respective vendor and Cradlepoint shall have no responsibility with regard to the selection, performance, or use of these products. All understandings, agreements, or warranties, if any, take place directly between the third-party vendor and the prospective user. Third-party products may be accompanied by their own terms of use, in which case those terms will govern use of that particular third-party product.

Additionally, Cradlepoint is not responsible for the content of any third-party linked site contained in this Guide. Your use of any such sites referenced in this Guide is at your own risk and will be governed by such third-party’s terms of use.

**EXCEPT AS WARRANTED IN A SEPARATE AGREEMENT, ALL INFORMATION IN THIS GUIDE IS PROVIDED “AS IS”, “WITH ALL FAULTS”, AND “AS AVAILABLE” WITH NO GUARANTEE ON COMPLETENESS, ACCURACY, TIMELINESS, OR OF THE RESULTS OBTAINED FROM USE OF THE INFORMATION. YOU BEAR THE RISK OF USING THIS GUIDE. CRADLEPOINT PROVIDES NO WARRANTIES, GUARANTEES OR CONDITIONS, WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, INCLUDING WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT. THESE DISCLAIMERS WILL APPLY TO THE FULLEST EXTENT PERMITTED UNDER APPLICABLE LAW, INCLUDING APPLICATION TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT.**

This Guide contains assistance for informational purposes only, and as such, may be revised or modified without notice.

## Intellectual Property

Cradlepoint® and the Cradlepoint logo are trademarks of Cradlepoint, Inc. All product and company names are trademarks of their respective holders. Use in this Guide does not imply any affiliation or endorsement by Cradlepoint.



## Table of Contents

<b>LIST OF TABLES .....</b>	<b>III</b>
<b>INTRODUCTION .....</b>	<b>1</b>
<b>BEST PRACTICES FOR SELECTING &amp; INSTALLING ANTENNAS ON CRADLEPOINT HARDWARE .....</b>	<b>1</b>
LTE, WI-FI, AND MIMO .....	1
CELLULAR RECEPTION .....	2
GNSS RECEPTION .....	2
CABLES & PORTS .....	3
POSITIONING ANTENNAS .....	3
<i>Antennas connected by cables .....</i>	<i>3</i>
<i>Paddle and direct attach antennas .....</i>	<i>3</i>
<b>FCC REGULATIONS .....</b>	<b>4</b>
IBR1700-1200M-B SPECIFIC REGULATIONS .....	4
IBR1700-600M SPECIFIC REGULATIONS.....	5
IBR900-1200M-B SPECIFIC REGULATIONS .....	6
IBR900-600M SPECIFIC REGULATIONS.....	7
IBR600C-150M-D SPECIFIC REGULATIONS .....	8
IBR600B-LP4 SPECIFIC REGULATIONS .....	9
<b>CRADLEPOINT ANTENNAS .....</b>	<b>10</b>
<b>CRADLEPOINT ANTENNA PROGRAM .....</b>	<b>11</b>
<b>APPROVED ANTENNA VENDORS .....</b>	<b>11</b>
APPROVED PANORAMA ANTENNAS .....	12
APPROVED PARSEC ANTENNAS .....	12
APPROVED TAOGLAS ANTENNAS .....	12
<b>APPENDIX A: PANORAMA .....</b>	<b>1</b>
<b>APPENDIX B: PARSEC.....</b>	<b>1</b>
<b>APPENDIX C: TAOGLAS .....</b>	<b>1</b>

# Antenna Reference Guide

---

## List of Tables

- Table 1. IBR1700-1200M-B Cellular Antennas - Maximum Gain by Frequency Range..... 4
- Table 2.. IBR1700-1200M-B Wi-Fi Antennas - Maximum Gain by Frequency Range..... 4
- Table 3. IBR1700-600M Cellular Antennas - Maximum Gain by Frequency Range. .... 5
- Table 4. IBR1700-600M Wi-Fi Antennas - Maximum Gain by Frequency Range. .... 5
- Table 5. IBR900-1200M-B Cellular Antennas - Maximum Gain by Frequency Range. .... 6
- Table 6. IBR900-1200M-B Wi-Fi Antennas - Maximum Gain by Frequency Range..... 6
- Table 7. IBR900-600M Cellular Antennas - Maximum Gain by Frequency Range. .... 7
- Table 8. IBR900-600M Wi-Fi Antennas - Maximum Gain by Frequency Range. .... 7
- Table 9. IBR600C-150M-D Cellular Antennas - Maximum Gain by Frequency Range. .... 8
- Table 10. IBR600C-150M-D Wi-Fi Antennas - Maximum Gain by Frequency Range. .... 8
- Table 11. IBR600B-LP4 Cellular Antennas - Maximum Gain by Frequency Range..... 9
- Table 12. IBR600B-LP4 Wi-Fi Antennas - Maximum Gain by Frequency Range..... 9
- Table 13. Cradlepoint Antennas..... 10



# Antenna Reference Guide

---

## Introduction

This antenna reference guide provides best practices for selecting and installing antennas with Cradlepoint hardware, regulations for specific Cradlepoint products to ensure FCC compliance, and references to supporting resources.

## Best Practices for Selecting & Installing Antennas on Cradlepoint Hardware

Cradlepoint endpoints are unique in their form and function and therefore not all antennas will be the best fit for each device. Cradlepoint recommends considering the following as you determine which antenna(s) will best suite your needs.

### LTE, Wi-Fi, and MIMO

Multiple Input, Multiple Output (MIMO) technologies, including LTE, 5G and Wi-Fi , enable all cellular and Wi-Fi antennas to send and receive data simultaneously. The best practice for both cellular and Wi-Fi antenna usage requires:

- Antenna include the full cellular or Wi-Fi frequency range capability that matches a given Cradlepoint device's capabilities.
- All antenna ports be occupied with a compatible antenna.

In addition to assuring optimal cellular and Wi-Fi performance, having all antenna ports occupied helps protect against future network changes that could impact compatibility.

Attaching only a portion of the cellular or Wi-Fi antennas impacts the device's functionality, up to and including reduced throughput, signal drops, and instability. For example, connecting two antennas on a Cradlepoint 2x2 MIMO modem may provide 40 Mbps throughput, compared to only connecting a single antenna, which could result in 15 Mbps. Additionally, the Cradlepoint device could experience connectivity issues such as completely dropping the cellular signal, either for periods of time, or as the modem is trying to cycle through available technologies (for example- fallback to 3G), up to and including fully disconnecting.

For customers that choose an antenna configuration not compliant with best practice, Cradlepoint will continue to provide best effort support until encountering a technical challenge identified as directly related to the antenna configuration. Such challenges may include changes (implemented by the network operator) affecting the use of cellular bands, newly required MIMO cellular communication, cellular frequencies put into use by a carrier network and modem not supported by the selected antenna, excessive noise, any of which could also cause a modem to fallback to a previous generation of cellular technology. Any of the above may also inhibit Cradlepoint Support's ability to engage beyond a reasonable effort and require the customer to change the model of antenna in use.

# Antenna Reference Guide

---

## Cellular Reception

Without sufficient cellular reception, the router may behave as though there are no antennas attached. The following describe how reception may be impacted:

- A paddle (direct attach) antenna is attached to a router inside of a metal box (i.e. kiosk) with no cellular reception
- A paddle (direct attach) antenna is used inside a building behind metal walls and/or brick with no reception
- A long coax cable with insufficient shielding/rating is run too far from the router
- Higher frequencies are more susceptible to signal loss when using longer cables
- Each coax cable fitting will add some signal loss.
- Actual dBm loss values are provided by the fitting manufacturer.
- The antenna does not support the frequency the device is trying to connect to
- Most antennas made before 2H 2019 or 2020 do not provide adequate gain for LTE bands 71 (600Mhz), 48/CBRS (3.5GHz) and/or 46/LAA (5GHz)
- NOTE: All of the antennas in the Cradlepoint Antenna Program are required to support all the frequencies of all our modems
- An antenna doesn't have proper separation from other radiation sources
- Example: Antennas from 2 radios that are simultaneously transmitting and receiving are positioned too close to each other and are de-sensing
- Direct attach paddle antennas aren't positioned for optimal reception
- Example: The antennas are laying on top of each other or not properly spaced
- An antenna has an insufficient ground plane to function properly
- Example: Mobile antennas are meant to be mounted on top of a metal roof with a sufficient ground plane to function properly. If mounted on a non-metallic surface or on a metal surface that is too small, they may provide insufficient gain.
- NOTE: Antenna spec sheets will call out if a ground plane is included or if needed and the minimum size.

Refer to <https://customer.cradlepoint.com/s/article/Modem-Signal-Strength-and-Signal-Quality> to determine if the signal strength is sufficient.

NOTE: Antenna types may be mixed and matched so long as they all have sufficient reception and do not exceed FCC regulations (i.e. remote/wired-out antennas for 2 LTE antenna ports on main/aux0 and GPS on the 1200M-B modem, and direct attached paddle antennas on main/aux1 of the 1200M-B modem and the Wi-Fi RP-SMA ports of an AER2200).

Refer to the FCC Regulations section of this guide for more information.

## GNSS Reception

Most customers use multi-purpose antennas that incorporate Wi-Fi, GNSS, and Cellular and have acceptable performance. However, for best performance, a physically separate GNSS antenna is required.

# Antenna Reference Guide

---

## Cables & Ports

The following are best practices for connecting antenna cables to the Cradlepoint ports:

- Ensure cable ends are connected to the correct ports.
- LTE and GPS ports use SMA connectors and WI-FI ports use RP-SMA. Check cable ends to ensure they are the appropriate connection type for the port you're attaching them to.
- GPS/GNSS connectors can be either active or passive. An active antenna requires an active port with suitable ratings to work. A passive antenna may be used on a passive port and can often be used on an active port, as long as the antenna is not a DC short-circuit type (e.g., Loop and PIFA antennas are typically DC short circuit).
- Do not over-torque the SMA connector on the modem. Finger-tight is sufficient (maximum torque is 4 in-lbs).
- Plan cable runs to minimize signal loss. Use the fewest number of coax cable fittings to avoid unnecessary signal loss.
- Coax cable has signal loss, especially for higher frequencies. For cable runs 15 feet or longer, use low loss LMR400. They generally connect using a larger, N-type connector, which requires a convertor to connect to the smaller SMA connectors on Cradlepoint endpoints.
- Use cable clamps or other cable-holding mechanisms to secure low-loss cables against a wall or pole.
- Use at least two clamps on the cable near the Cradlepoint endpoint. This construction helps reduce stress on the cable/modem connection and increases product reliability.
- Use lightning protection.

## Positioning Antennas

To avoid signal loss, ensure the appropriate cables and direct attach antennas are connected to their applicable ports on the Cradlepoint endpoint.

### **Antennas connected by cables**

Ensure the antennas are installed according to the manufacturer's installation requirements and that the power, gain, and other applicable signal settings are configured in compliance with the specifications dictated in the Antenna selection guide.

### **Paddle and direct attach antennas**

Stagger the angles of the paddles so that they are not in alignment with each other. Use the antenna alignment tool with applicable endpoints. For positioning examples, refer to [How to Position 1200M Antennas](#).

# Antenna Reference Guide

## FCC Regulations

The FCC requires that antennas attached to Cradlepoint products meet certain standards. Using antennas not sold by Cradlepoint places the burden of confirming that the antenna meets FCC regulations on the customer. The following specifies the acceptable frequency ranges, antenna types, and gains to assist with identifying third party antennas to use with specific Cradlepoint products.

### IBR1700-1200M-B Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include 1200M-B modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 1. IBR1700-1200M-B Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
617-698 MHz	9 dBi
699-787 MHz	6 dBi
788-798 MHz	6.4 dBi
1710-1785 MHz	5.5 dBi
1850-1920 MHz	8.51 dBi
2000-2020 MHz	9 dBi
2300-2400 MHz*	1.08 dBi
2496-2690 MHz	5.5 dBi

\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.

Antennas connected to the Wi-Fi ports on IBR1700 series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 2. IBR1700-1200M-B Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Other Antennas
2402-2843.5 MHz	5 dBi	Not allowed
5150-5250 MHz	5 dBi	Not allowed
5250-5350 MHz	5 dBi	Not allowed
5475-5725 MHz	5 dBi	Not allowed
5725-5850 MHz	5 dBi	Not allowed



# Antenna Reference Guide

## IBR1700-600M Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include 600M modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 3. IBR1700-600M Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
600-800 MHz	Cannot exceed FCC EIRP Limits
800-1000 MHz	Cannot exceed FCC EIRP Limits
1700-1800 MHz	Cannot exceed FCC EIRP Limits
1800-2000 MHz	Cannot exceed FCC EIRP Limits
2300-2400 MHz*	1.0 dBi
2500-2600 MHz	Cannot exceed FCC EIRP Limits

\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.

Antennas connected to the Wi-Fi ports on IBR1700 series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 4. IBR1700-600M Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Other Antennas
2402-2843.5 MHz	5 dBi	Not allowed
5150-5250 MHz	5 dBi	Not allowed
5250-5350 MHz	5 dBi	Not allowed
5475-5725 MHz	5 dBi	Not allowed
5725-5850 MHz	5 dBi	Not allowed

# Antenna Reference Guide

## IBR900-1200M-B Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include 1200M-B modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 5. IBR900-1200M-B Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
617-698 MHz	9 dBi
699-787 MHz	6 dBi
788-798 MHz	6.4 dBi
1710-1785 MHz	5.5 dBi
1850-1920 MHz	8.51 dBi
2000-2020 MHz	9 dBi
2300-2400 MHz*	1.08 dBi
2496-2690 MHz	5.5 dBi

\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.

Antennas connected to the Wi-Fi ports on IBR900 series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 6. IBR900-1200M-B Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Monopole Antennas	PIFA antennas	Other Antennas
2402-2843.5 MHz	2.47 dBi	1.5 dBi	1.5 dBi	Not allowed
5150-5250 MHz	2.47 dBi	1.0 dBi	2 dBi	Not allowed
5250-5350 MHz	2.47 dBi	1.0 dBi	2 dBi	Not allowed
5475-5725 MHz	2.47 dBi	0.9 dBi	1.9 dBi	Not allowed
5725-5850 MHz	2.47 dBi	0.9 dBi	1.9 dBi	Not allowed

# Antenna Reference Guide

## IBR900-600M Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include 600M modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 7. IBR900-600M Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
600-800 MHz	Cannot exceed FCC EIRP Limits
800-1000 MHz	Cannot exceed FCC EIRP Limits
1700-1800 MHz	Cannot exceed FCC EIRP Limits
1800-2000 MHz	Cannot exceed FCC EIRP Limits
2300-2400 MHz*	1.0 dBi
2500-2600 MHz	Cannot exceed FCC EIRP Limits

\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.

Antennas connected to the Wi-Fi ports on IBR900 series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 8. IBR900-600M Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Monopole Antennas	PIFA antennas	Other Antennas
2402-2843.5 MHz	2.47 dBi	1.5 dBi	1.5 dBi	Not allowed
5150-5250 MHz	2.47 dBi	1.0 dBi	2 dBi	Not allowed
5250-5350 MHz	2.47 dBi	1.0 dBi	2 dBi	Not allowed
5475-5725 MHz	2.47 dBi	0.9 dBi	1.9 dBi	Not allowed
5725-5850 MHz	2.47 dBi	0.9 dBi	1.9 dBi	Not allowed

# Antenna Reference Guide

## IBR600C-150M-D Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include 150M-D modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 9. IBR600C-150M-D Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
617-698 MHz	8.55 dBi
699-787 MHz	8.55 dBi
788-798 MHz	8.73 dBi
1710-1785 MHz	5 dBi
1850-1920 MHz	8 dBi
2000-2020 MHz	9 dBi
2300-2400 MHz*	1.08 dBi

\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.

Antennas connected to the Wi-Fi ports on IBR900 series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 10. IBR600C-150M-D Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Monopole Antennas	PIFA antennas	Other Antennas
2402-2843.5 MHz	2.47 dBi	1.5 dBi	1.5 dBi	Not allowed

# Antenna Reference Guide

## IBR600B-LP4 Specific Regulations

Antennas connected to the MAIN and AUX ports on products that include LP4 modems must have a system gain (antenna gain minus cable loss) less than the following values:

Table 11. IBR600B-LP4 Cellular Antennas - Maximum Gain by Frequency Range.

Frequency	Maximum Gain
777-862 MHz	9.72 dBi
1710-1785 MHz	5.78 dBi
1850-1920 MHz	7.51 dBi

*\*Operation in the 2300-2400 MHz band is allowed indoors only, and the antenna must be more than 50' from any roadway. If the antenna is installed outdoors, within 50' of any roadway, or if the antenna system gain is greater than 1.08 dBi in this band, the installer must disable LTE Band 30 in the Connection Manager>Modem properties>Modem tab.*

Antennas connected to the Wi-Fi ports on IBR600B series devices must have system gain (antenna gain minus cable loss) less than the following values:

Table 12. IBR600B-LP4 Wi-Fi Antennas - Maximum Gain by Frequency Range.

Frequency	Dipole Antennas	Other Antennas
2402-2843.5 MHz	5.0 dBi	Not allowed

# Antenna Reference Guide

## Cradlepoint Antennas

Cradlepoint carries a limited selection of antennas for use with Cradlepoint products. Refer to the following table for more information.

Table 13. Cradlepoint Antennas.

Part Number	Description	Compatible Products
170659-001	Cellular Antenna, White, 700MHz - 2.7GHz, SMA, 210mm	Used with, CBA850-LP6, CBA850-LP4
170706-000	Cellular Antenna, Black, 700MHz - 2.7GHz, SMA, 160mm	Used with, LP6 modems, LP4 modems
170704-002	Cellular Antenna, Black mini, 600MHz - 6GHz, SMA, 140mm	Used with, 600M, 150M, 10M modems
170761-001	Cellular Antenna, White, 600MHz - 6GHz, SMA, 180mm	Used with, CBA850-1200M-B, W2000
170765-000	Cellular Antenna, White mini, 600MHz - 4.2GHz, SMA, 145mm	Used with, CBA550, L950
170801-000	Cellular Antenna, Charcoal, 600MHz - 6MHz, SMA, 180mm	Used with, E300, E3000, MC400, 1200M-B
170836-000	Wi-Fi Antenna, Charcoal, Dual-band 2.4/5GHz, RPSMA, 194mm	Used with, All Wi-Fi products

# Antenna Reference Guide

---

## Cradlepoint Antenna Program

The Cradlepoint Antenna Program consists of antennas provided by vendors who have met the requirements to be included in the program. The program establishes a specific set of criteria to ensure the antennas meet compatibility and regulatory standards, including:

- Frequency range: 600MHz – 6 GHz with minimum 10 MHz steps
- Supporting technical documents including data sheets and installation guides
- Support for the Cradlepoint Support team and Cradlepoint customers
- Marketing materials

The program replaces the previous selection and sales process by connecting customers with our approved vendors to find and purchase the antenna(s) that best meet their needs. This allows our sales teams and partners more options and the newest antennas as they are made available from the vendors.

The approved antenna vendors will manage customer antenna purchases, with the exception of specific antennas (and their replacements) that Cradlepoint provides as part of certain subscription packages.

While there are many quality antenna vendors, Cradlepoint cannot qualify and approve them all. If customers choose to use other antenna vendors or other antennas not currently listed on the approved antenna tables in this document, they are responsible for qualifying their performance to meet FCC regulations. Cradlepoint will be unable to troubleshoot non-approved antennas.

For support-related customer service, Cradlepoint Support will follow the standard procedure for troubleshooting and diagnosing endpoint connectivity issues. If the issue appears to be related to the antenna (i.e., poor signal strength, drops, poor throughput, etc.) the customer may be asked to connect an approved antenna before further debugging.

Vendors interested in the program must be recommended by Cradlepoint sales team members, partners, or customers and have an established, consistently positive relationship with them. Recommended vendors are communicated through Cradlepoint internal requests only. External requests will not be considered.

## Approved Antenna Vendors

The following are the Approved Antenna Vendors in the Cradlepoint Antenna Program. This section includes lists of each vendor's antennas approved to work with Cradlepoint products and the required cable lengths to meet FCC compliance. For vendor contact information, refer to the appendices in this document.



NOTE: The column that delineates between installations with or without ground planes refers to the following scenarios:

- **W/ ground plane:** When the antenna is installed on a metal surface (aluminum, steel, etc.), 1 to 1 1/4 ft larger than the size of the antenna or greater.
- **W/O ground plane:** When the antenna is installed on any non-metallic surface (such as fiberglass).

---

## Approved Panorama Antennas

Click on the link below to view all of the Cradlepoint Approved, Panorama Antennas.

[Cradlepoint Approved Panorama Antennas](#)

For contact information refer to Appendix A: Panorama.



## Approved Parsec Antennas

Click on the link below to view all of the Cradlepoint Approved, Parsec Antennas.

[Cradlepoint Approved Parsec Antennas](#)

For contact information, refer to Appendix B: Parsec.



## Approved Taoglas Antennas

Click on the link below to view all of the Cradlepoint Approved, Taoglas Antennas.

[Cradlepoint Approved Taoglas Antennas](#)

For contact information, refer to Appendix C: Taoglas.





# Antenna Reference Guide



## Appendix A: Panorama

[www.panorama-antennas.com/cradlepoint](http://www.panorama-antennas.com/cradlepoint)

General Support: [817-539-1888](tel:817-539-1888)  
[Global Support options](#)

Rep	Title	Email	Phone	Region(s)	
Bryan McAnally	Regional Account Manager	bmcanally@panorama-antennas.com	C: 817-706-8636 O: 817-225-4779	Alaska (AK) Idaho (ID) Kansas (KS) Montana (MT) Nebraska (NE)	North Dakota (ND) Oklahoma (OK) Oregon (OR) South Dakota (SD) Washington (WA)
Hans Giraud	Regional Account Manager	hgiraud@panorama-antennas.com	C: 818-512-1878 O: 817-225-4784	Arizona (AZ) Colorado (CO) New Mexico (NM)	Utah (UT) West Texas (W.TX) Wyoming (WY)
Mark Frazier	Regional Account Manager	mfrazier@panorama-antennas.com	C: 214-808-5663	Illinois (IL) Indiana (IN) Iowa (IA) Michigan (MI)	Minnesota (MN) Ohio (OH) Wisconsin (WI)
Trey Gaddy	Regional Account Manager	tgaddy@panorama-antennas.com	C: 214-415-7685 O: 817-225-4783	Alabama (AL) Arkansas (AR) Florida (FL) Georgia (GA)	Louisiana (LA) Mississippi (MS) Missouri (MO)
Rahmin Massudi	Regional Account Manager	rmassudi@panorama-antennas.com	C: 817-944-6321 O: 817-225-4781	Texas (TX), excluding West Texas	
Rick Azevedo	Regional Account Manager	razevedo@panorama-antennas.com	C: 915-799-9505 O: 817-225-4780	Connecticut (CT) Maine (ME) Massachusetts (MA) New Hampshire (NH) New Jersey (NJ)	New York (NY), excluding Upstate New York Pennsylvania (PA) Rhode Island (RI) Vermont (VT)
Leann LeHew	Regional Account Manager	llehew@panorama-antennas.com	C: 469-536-2277 O: 817-225-4778	Delaware (DE) District of Columbia (DC) Kentucky (KY) Maryland (MD)	South Carolina (SC) Tennessee (TN) Virginia (VA) West Virginia (WV)
Travis Culwell	Regional Account Manager	tculwell@panorama-antennas.com	C: 972-965-0663 O: 817-225-4787	California (CA) Hawaii (HI)	Nevada (NV)
Wil Hoyle	Head of Sales & Business - Canada	whoyle@panorama-antennas.com	C: 289-387-3126	Canada (CA)	Upstate New York (NY)
Lee Jackson	Head of Sales & Business - N.A.	ljackson@panorama-antennas.com	C: 817-312-8897 O: 817-225-4782		
Thierry Vienney	Sales & Business Development	tvienney@panorama-antennas.com	+33 6 72 54 04 74	France	Italy
Piia Korhonen	Area Sales Manager	pkorhonen@panorama-antennas.com	+34 662 670 320	Spain	Portugal
Torbjørn Barfod	Area Sales Manager	tbarfod@panorama-antennas.com	+45 40 11 88 02	Scandinavia	Eastern Europe
Nestor Figueroa	Area Sales Manager	nfigueroa@panorama-antennas.com	+57 304 205 8157	Central & South America	Mexico
Christian Cielinski	Area Sales Manager	ccielinski@panorama-antennas.com	+49 163 494 5925	Germany Austria	Switzerland
Ken Pattison	Area Sales Manager	kpattison@panorama-antennas.com	+44 7785 303740	United Kingdom Belgium	The Netherlands Middle East
Robert Jesman	Sales Director	rjesman@panorama-antennas.com	+44 789 9988050	Australia, New Zealand Malaysia, Singapore	South Africa South East Asia Hong Kong

# Antenna Reference Guide

---

Panorama International distribution:

- Bluestar Canada
- Synnex Canada
- Exclusive
- Westbase
- Tech Data ANZ
- Go Wireless

# Antenna Reference Guide



## Appendix B: Parsec

<https://parsec-t.com/cradlepoint-approved-antennas/>

General Support: 972-804-4600  
[support@parsec-t.com](mailto:support@parsec-t.com)

Rep	Title	Email	Phone	Regions
Corporate Office	All new customers	sales@parsec-t.com	972-804-4600 (Press 1 for Sales)	All
George Girvin	Senior Director - Business Development - Central U.S.	George.Girvan@parsec-t.com	469-814-8280	Canada - Central CO,IL,IN,IA,KS,KY,MI,MN,MO, NE,ND,OH,SD,WI
Cinthia Oviedo	Sales Assistant - - Central and East U.S.	Cinthia.Oviedo@parsec-t.com	972-698-4018	AL,CT,FL,GA,IL,IN,KY,ME,MD,MA,MI,MS,NH,NJ,NY,NC,OH,PA,RI,SC,TN,VT,VA,WV,WI,
Kelsey Guillory	Sales Assistant - Cental and West U.S.	Kelsey.Guillory@parsec-t.com	469-808-9030	AK,AZ,AR,CA,CO,HI,ID,IA,KS,LA,MN,MO,MT,ND,NE,NM,NV,OK,OR,SD,TX,UT,WA,WY Canada - West
Jack Neenan	Senior sales Director - North East US	jack.neenan@parsec-t.com	401-287-7737	Canada - East, CT,DE,ME,MD,MA,NH,NJ,NY,PA,RI,VT
Melissa Heckel	Partner Relations Manager	melissa.heckel@parsec-t.com	469-229-7905	All Regions
Jen Neenan	COO	jen.neenan@parsec-t.com	972-804-4808	All-- Sales for Europe and Latin America
Michael Neenan	CEO	mneenan@parsec-t.com	972-535-5501	All - Sales for Asia-Pacific and Africa

Parsec International distribution:

- Westbase
- Tech Data
- Ingram Micro

# Antenna Reference Guide



## Appendix C: Taoglas

<https://www.taoglas.com/taoglas-antenna-reference-guide/cradlepoint/>

General Support: <https://www.taoglas.com/contact/>

Rep	Title	Email	Phone	Region(s)	
Tim Dolan	Sales & Support – Northeast & Southeast	tdolan@taoglas.com	978-430-2711	Montreal Toronto Connecticut (CT) Delaware (DE) Indiana (IN) Maine (ME) Maryland (MD) Massachusetts (MA) Michigan (MI) Alabama (AL) Florida (FL) Georgia (GA) Kentucky (KY) Louisiana (LA)	New Hampshire (NH) New Jersey (NJ) New York (NY) Ohio (OH) Pennsylvania (PA) Rhode Island (RI) Vermont (VT) Virginia (VA) West Virginia (WV) Mississippi (MS) North Carolina (NC) South Carolina (SC) Tennessee (TN)
Arturo Proskauer	Sales & Support – Central and South America (except Brazil)	aproskauer@taoglas.com	619-618-8946	Central America, Mexico, Brazil	South America Mexico
Samuel McCarthy	Sales & Support – EMEA	smccarthy@taoglas.com	+353 53 9169500	Austria Germany	Poland Switzerland
Rebecca Slevin	Sales & Support – APAC	rslevin@taoglas.com	+886 3 3681223 +86 (755) 86538292	Taiwan – Asia China Malaysia Singapore	Australia New Zealand
Helen Liang	Sales & Support – APAC	hliang@taoglas.com			
Prakash Patil	Sales & Support – India	ppatil@taoglas.com		India	
Taylor Kimmerle	Distribution Partner	tkimmerle@taoglas.com			
Jonathan Nagle	Reseller	jnagle@taoglas.com			
Jeff Clark	Director of Public Safety Sales	jclark@taoglas.com	940-799-1846	United States	

Taoglas International distribution:

- Westbase