

## Ursalink Product Models – Powertec Telecommunications

<b>Routers</b>	<b>UR32-L00AU-W</b>	<b>UR35-L00AU-W</b>	<b>UR35-L00AU-W-G-P</b>	<b>UR35-L00AU-W-S</b>
<b>WIRELESS</b>	M2M-UR-00009	M2M-UR-00010	M2M-UR-00011	M2M-UR-00012
<b>Cellular Technology</b>	CAT4 – 3G/4G	CAT4 – 3G/4G	CAT4 – 3G/4G	CAT4 – 3G/4G
<b>WiFi</b>	2.4 GHz (b/g/n)	2.4 GHz (b/g/n)	2.4 GHz (b/g/n)	2.4 GHz (b/g/n)
<b>GPS</b>			✓	
<b>Bluetooth</b>				
<b>PORTS</b>				
<b>Ethernet Ports</b>	2 x 10/100	5 x 10/100	5 x 10/100 + PoE PSE	5 x 10/100
<b>LAN/WAN</b>	1x WAN + 1x LAN OR 2x LAN	1x WAN + 4x LAN	1x WAN + 4x LAN	1x WAN + 4x LAN
<b>WAN Failover</b>	WAN + 2 <sup>nd</sup> Sim	WAN + 2 <sup>nd</sup> Sim	WAN + 2 <sup>nd</sup> Sim	WAN + 2 <sup>nd</sup> Sim
<b>RS232</b>	✓	✓	✓	✓
<b>RS485</b>			✓	
<b>Digital I/O</b>	1 x In, 1 x Out	1 x In, 1 x Out	1 x In, 1 x Out	1 x In, 1 x Out
<b>Analog Input</b>				
<b>USB</b>				
<b>Mobile antenna</b>	2x SMA	2x SMA	2x SMA	2x SMA
<b>WiFi antenna</b>	1x RP-SMA	1x SMA	1x SMA	1x SMA
<b>GPS antenna</b>			1x SMA	
<b>Voice Port (FXS)</b>				1 x RJ11
<b>PROCESSING</b>				
<b>CPU</b>	528 MHz	528 MHz	528 MHz	528 MHz
<b>RAM</b>	128 MB	128 MB	128 MB	128 MB
<b>Flash Memory</b>	128 MB	128 MB	128 MB	128 MB
<b>SLOTS</b>				
<b>SIM card slots</b>	2x 2FF	2x 2FF	2x 2FF	2x 2FF
<b>Micro SD Slot</b>	✓	✓	✓	✓